

CE-20

Chorus Ensemble

**BOSS®**

BOSS' Ultimate Chorus Pedal.

The CE-20 Chorus Ensemble is the culmination of over 25 years of BOSS chorus experience. This programmable chorus pedal not only models classics like the CE-1 and SDD-320, but creates entirely new effects including chorus for bass and acoustic guitar. New “Brilliance” and “Ambience” knobs offer unprecedented realtime control over the chorus tone—making the CE-20 a pedal no guitarist should be without.

- BOSS' finest chorus effects ever offered in a compact pedal
- 6 chorus modes: Rich, Bass, Acoustic, Standard, CE-1 and Dimensional D
- Brilliance parameter adjusts “sparkling” feel of chorus
- Ambience control adds reverberation to chorus for greater spaciousness
- 4 User memories with pedal recall
- Stereo In/Out and Headphone output



Classic and Modern Chorus Sounds

As the creator of the chorus pedal, no one knows chorus better than BOSS. That's why the CE-20 includes six chorus modes covering classic sounds from the CE-1 and SDD-320 to modern chorus effects. Three new types of chorus are also provided, for getting everything from extremely rich sounds to chorus tuned specifically for bass and acoustic guitar.

New “Brilliance” and “Ambience” Controls

Using the Brilliance knob, you can control the “sparkling” feel of the CE-20's chorus sounds for effects that really cut through the mix. The secret is the CE-20's unique ability to enhance a guitar's harmonics. Another new control is the Ambience knob, which adds reverberation to the chorus for even greater spaciousness and depth. There's never been a sound like it!

*Actual product appearance may be subject to change without notice.

CE-20 Specifications

● **Nominal Input Level** -20 dBu (GUITAR/BASS), +4 dBu (AMPLIFIER SEND/RETURN) ● **Input Impedance** 1 M Ω
● **Nominal Output Level** -20 dBu (GUITAR/BASS), +4 dBu (AMPLIFIER SEND/RETURN) ● **Output Impedance** 1 k Ω (OUTPUT R (MONO), L), 33 Ω (PHONES) ● **Recommended Load Impedance** 10 k Ω ● **Residual Noise Level** -93 dBu or less (IHF-A typ.) ● **Controls** EFFECT ON/OFF Pedal, MANUAL/MEMORY Pedal, E.LEVEL Knob, LOW Knob, HIGH Knob, BRILLIANCE Knob, AMBIENCE Knob, MODE Knob, RATE Knob, DEPTH Knob, MEMORY WRITE Button, MEMORY SELECT Button, LEVEL Switch ● **Indicators** POWER Indicator (serves also as battery check indicator), EFFECT ON/OFF Indicator, MANUAL Indicator, MEMORY Indicator, PEAK Indicator, RATE Indicator, MEMORY Number Indicator 1—4 ● **Connectors** INPUT Jacks (R (MONO), L) (1/4 inch phone type), PHONES Jack (stereo 1/4 inch phone type), OUTPUT Jacks (R (MONO), L) (1/4 inch phone type), AC Adaptor Jack ● **Power** Dry battery (R6/LR6 (AA) type) x 6: DC 9V, AC Adaptor (DC 9V) ● **Current draw** 160 mA (9 V max.)* Expected battery life under continuous use: Carbon: 4 hours, Alkaline: 10 hours These figures will vary depending on the actual conditions of use. ● **Dimensions** 173 (W) x 158 (D) x 57 (H) mm, 6-13/16 (W) x 6-1/4 (D) x 2-1/4 (H) inches ● **Weight** 1.1 kg / 2 lbs 7 oz (including batteries) ● **Accessories** Owner's Manual Leaflet (“USING THE UNIT SAFELY,” “IMPORTANT NOTES,” and “Information”) Dry battery (LR6 (AA) type) x 6 * We recommend that alkaline batteries be used when replacing the batteries. ● **Options** AC Adaptor (PSA-series)

* 0 dBu = 0.775 Vrms.

* The specifications are subject to change without notice.