



## XLS SERIES

# XLS 202

## Architectural & Engineering Specifications

### XLS 202 (120 V, 60 Hz models)

The power amplifier shall be a solid-state two-channel model.

The amplifier shall provide extensive protection and diagnostic capabilities, including output current limiting, DC protection, circuit breaker, and special thermal protection for the unit's transformers.

The front-panel controls shall be two black detented level controls (one for each channel), a power switch, and a circuit breaker for overload protection.

Front-mounted indicators shall be Clip: one red LED per channel which illuminates when the channel's output signal is being overdriven, Power: one green LED which indicates that the amplifier has been turned on and AC power is available, and Fault: one yellow LED which illuminates when amplifier is in protect mode and briefly during normal power-up when amplifier is first switched on.

The recommended load impedance shall be 2 to 8 ohms per channel in Stereo, and 8 ohms in Bridge Mono. The amplifier shall be safe when driving any kind of load, including highly reactive ones.

The rear-mounted output connectors shall be two 4-pole Speakon® connectors (one per channel) and a pair of 5-way binding posts per channel. Rear-mounted input connectors shall be 3-pin balanced XLR connectors.

The power amplifier shall meet or exceed the following performance criteria: Input sensitivity for rated output at 4 ohms: 0.725 V. Rated output with both channels driven with 0.5% THD (at 1 kHz) in Dual mode: 250 watts per channel into 2 ohms, 200 watts per channel into 4 ohms, and 145 watts per channel into 8 ohms. Rated output with 0.5% THD (at 1 kHz) in Bridge-Mono mode: 400 watts into 8 ohms and 500 watts into 4 ohms. Frequency Response at 1 watt, 20 Hz to 20 kHz:  $\pm 0.75$  dB. Phase Response at 1 watt:  $-10$  degrees at 10 Hz,  $+19$  degrees at 20 kHz. Signal to Noise Ratio below rated power (20 Hz to 20 kHz): greater than 100 dB A-weighted. Total Harmonic Distortion at full rated power, 1 kHz: less than 0.15%. Intermodulation Distortion (60 Hz and 7 kHz at 4:1, from full rated output to  $-40$  dB: less than 0.3%. Damping Factor (8 ohms): greater than 200 from 10 to 400 Hz. Crosstalk (below rated power,  $-82$  dB at 1 kHz,  $-58$  dB at 20 kHz. Voltage Gain at maximum output: 31 dB. Input Impedance (nominal): 20 kilohms balanced, 10 kilohms unbalanced. AC Line Voltages and Frequencies Available ( $\pm 10\%$ ): 120 VAC/60Hz and 230 VAC/50 Hz.

The amplifier chassis shall be constructed of steel with a durable black finish and shall be designed for flow-through ventilation from the front panel to the back panel. Internal heat sinks with forced-air cooling shall provide rapid, uniform heat dissipation.

The dimensions of the amplifier shall allow for 19 inch (48.3 cm) EIA standard (RS-310-B) rack mounting. The amplifier shall be 3.5 inches (8.9 cm) tall, and 14 inches (35.6 cm) deep behind the rack-mounting surface.

The amplifier shall weigh 21.0 pounds (9.5 kg).

The amplifier shall be designated the Crown XLS 202.



**H** A Harman International Company

Crown International  
P.O. Box 1000  
Elkhart, IN 46515-1000  
TEL: 574-294-8200  
FAX: 574-294-8FAX  
[www.crownaudio.com](http://www.crownaudio.com)

Specifications subject to change without prior notice. Latest information available at [www.crownaudio.com](http://www.crownaudio.com).  
Crown and Crown Audio are registered trademarks of Crown International. Other trademarks are the property of their respective owners.  
Printed in U.S.A.