

Bugera

THE SOUL OF VALVES

6262-212
Specifications

BUGERA 6262-212

Boutique-Style 120-Watt 2-Channel Valve Combo with Reverb

- ◆ Hand-built 120-Watt guitar combo driven by 4 x 6L6 valves (convertible to EL34)
- ◆ 2 original heavy-duty 12" BUGERA guitar speakers for true vintage sound
- ◆ Classic 2-channel preamp design (Clean, Crunch, Lead) featuring 6 x 12AX7 valves for terrifying punch and mind-blowing gain
- ◆ Integrated high-class reverb with dedicated Reverb control for each channel
- ◆ Independent Equalizer sections for each channel with dedicated Bass, Mid and Treble controls
- ◆ Classic Presence control per channel for awesome sound shaping
- ◆ Impedance switch (4, 8 and 16 Ohms) to match virtually any speaker cabinet
- ◆ FX Loop with independent Send and Return level controls also serves as Boost function
- ◆ Heavy-duty footswitch for Channel selection and FX Loop function included
- ◆ High-quality components and exceptionally rugged construction ensure long life

Specifications

PREAMP SECTION

Valves

Type	2 x 12AX7A 4 x 12AX7
------	-------------------------

Preamp high-gain input

Impedance	470 k Ω
-----------	----------------

Clean channel

Nominal input level	-34 dBV
Min. input level	-50 dBV
Max. input level	0 dBV

Lead channel

Nominal input level	-80 dBV
Min. input level	-92 dBV

Effects send

Impedance	47 k Ω or higher
Nominal output level	-10 dBV

Effects return

Impedance	470 k Ω
Min. input sensitivity	-10 dBV

Preamp output

Impedance	47 k Ω or higher
Nominal output level	+10 dBV

POWER AMPLIFIER SECTION

Valves

Type	4 x 6L6GC
------	-----------

Output power

Peak power	120 W / 16, 8, 4 Ω
------------	---------------------------

Loudspeaker connectors

Type	¼" mono jack connectors, unbalanced
Load impedance	4 Ω / 8 Ω / 16 Ω switchable

Internal loudspeakers

Type	2 x 12" BUGERA, 12G70J8
Impedance	8 Ω
Power	70 W (IEC)
Total impedance	16 Ω (series connection)

POWER SUPPLY

Power consumption	Max. 350 W
Fuse	T 3.15 A H 250 V (100 – 120 V~, 50/60 Hz) T 1.6 A H 250 V (220 – 240 V~, 50/60 Hz)
Mains connection	Standard IEC receptacle

DIMENSIONS/WEIGHT

Dimensions (H x W x D)	Approx. 20 13/32" x 27" x 9 3/4" (518.46 mm x 687.3 mm x 247.65 mm)
Weight	Approx. 63 lbs (28.5 kg)

We are constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to time to existing products without prior notice. Specifications and appearance may differ from those listed or illustrated.

Technical specifications and appearance are subject to change without notice. The information contained herein is correct at the time of printing. All trademarks (except BUGERA, the BUGERA logo, and THE SOUL OF VALVES) mentioned belong to their respective owners, and such use neither constitutes a claim of the trademarks by RED CHIP COMPANY LTD nor affiliation of the trademark owners with RED CHIP COMPANY LTD. RED CHIP COMPANY LTD accepts no liability for any loss which may be suffered by any person who relies either wholly or in part upon any description, photograph or statement contained herein. Colors and specifications may vary slightly from product. Our Products are sold through authorized dealers only. This manual is copyrighted. No part of this manual may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording of any kind, for any purpose, without the express written permission of RED CHIP COMPANY LTD. BUGERA-products are distributed exclusively by the BEHRINGER Group of companies globally, and specifically by BEHRINGER International GmbH in the European Union.

ALL RIGHTS RESERVED.
(c) 2007 RED CHIP COMPANY LTD.
Trident Chambers, Wickhams Cay, P.O. Box 146,
Road Town, Tortola, British Virgin Islands.