

	End of DB25 Cable	Other End of DB25 Cable	
	<u>Pin #</u>	<u>Pin #</u>	
CH 1/2 Out +	18	24	CH 1/2 In +
CH 1/2 Out -	6	12	CH 1/2 In -
GND	19	25	GND
CH 3/4 Out +	4	10	CH 3/4 In -
CH 3/4 Out -	17	23	CH 3/4 In -
GND	5	11	GND
CH 5/6 Out +	15	21	CH 5/6 In +
CH 5/6 Out -	3	9	CH 5/6 In -
GND	16	22	GND
CH 7/8 Out +	1	7	CH 7/8 In +
CH 7/8 Out -	14	20	CH 7/8 In -
GND	2	8	GND
CH 1/2 In +	24	18	CH 1/2 Out +
CH 1/2 In -	12	6	CH 1/2 Out -
GND	25	19	GND
CH 3/4 In +	10	4	CH 3/4 Out -
CH 3/4 In -	23	17	CH 3/4 Out -
GND	11	5	GND
CH 5/6 In +	21	15	CH 5/6 Out +
CH 5/6 In -	9	3	CH 5/6 Out -
GND	22	16	GND
CH 7/8 In +	7	1	CH 7/8 Out +
CH 7/8 In -	20	14	CH 7/8 Out -
GND	8	2	GND
not connected	13	13	not connected