

WMS40 PRO FLEXX frequencies				simultaneously usable channels															
BAND 40 / .	country/TV channel	PANTONE Color Code	Frequency	6	6	7	8	6	9	3	3	5	6	9	3	3	4	4	3
				Germany ISM + TV62 NG4				Germany ISM + TV63 NG4				France ISM + TV44/45 Series 3				USA			
A	US45	Cool Gray 2	F [MHz]	A1 660,700				x	x			x	x						
				A2 661,100				x	x			x	x						
				A3 662,300				x	x			x	x						
B	US58	1235C melon yellow		B1 734,600										x					
				B2 736,025										x					
				B3 736,975										x					
C	US60	2736C violet		C1 748,875										x	x	x			
				C2 750,900										x	x	x			
				C3 751,550										x	x	x			
D	EU62/DE NG4	285C skyblue		D1 802,525	x		x	x									x	x	x
				D2 803,025	x			x									x		x
				D3 805,100	x	x	x										x	x	x
E	EU63/JP B + DE/NG4	375C yellowgreen		E1 806,875	x		(x)									x			
				E2 808,625	x											x			
				E3 809,125	x											x			
F	EU63/DE NG4	354U2x green		F1 812,800		x	(x)										(x)	x	
				F2 813,100														x	
				F3 813,800		x													
G	EU63/FR series 3	513C dark purple		G1 812,700					x										
				G2 813,100					x										
				G3 815,000				x											
H	UK69 shared	2708C light blue		H1 854,900						x		x	(x)						
				H2 855,900					x		x	x							
				H3 857,625					x		x	x							
ISM	EU ISM 863-865MHz	444C darkgray	ISM1	863,100	x	x	x	x	x	x	x	x							
			ISM2	864,375	x	x	x	x	x	x	x	x	x	x					
			ISM3	864,850	x	x	x	x	x	x	x	x	x	x	x				

(x) when using this frequency in multichannel applications, distance to the next receiver must be > 1m

Please note: BAND 40/F is designed as complementary band for multichannel use only