

Macintosh Installation Guide

Requirements

To use mLAN, you need the following:

A Macintosh computer with OS9.x installed. An IEEE1394 Port is also required.

(Recommended) 800 MHz or faster processor with 256 MB RAM.

Installation

It is strongly recommended that you exit all programs and remove all mLAN equipment from your computer before running this Setup Program.

mLAN Driver Installation

1. Go to the provided CD-ROM, open the MAC Folder and double click the .SIT file
2. Choose the target directory for the expansion (or create one)
3. Double click the installer
4. After the installer has run, reboot
5. Copy the ASIO mlan driver to the ASIO folder of your recording software
6. Connect the FIREstation

mLAN OMS Installation

1. Install OMS
2. Drag and Drop the "OMS mLAN" file into the "OMS" folder inside the "System" folder
3. Start the OMS Setup application and select "MIDI Cards and Interfaces..." from the "Studio" menu, mLAN icons equivalent to the number of installed FireWire (IEEE1394) interface cards appear
4. OMS regards mLAN as a MIDI interface. Therefore, to transmit and receive MIDI data, select "Studio" then "New Device..." and create a number of devices to match the number of ports used by mLAN, and connect them under the mLAN device. It is a good idea to name these devices, for example, as "mLAN port 1," "mLAN port 2," etc