

Eliminator® LIGHTING

EF 400

400 WATT FOG MACHINE

CAUTION! Please read and understand these instructions before installing or operating this unit.

SPECIFICATIONS:

Model:	EF 400
Voltage:	120v
Weight:	5Lbs./2.2Kgs.
Size:	8.5"(L) x 6"(W) x 6"(H)
Fuse:	4 Amp
Fluid Type:	Eliminator Brand Water Based Fog Juice
Heater:	400 Watts
Output:	1,500 cubic ft. per minute
Warranty:	1 Year Limited Warranty

Operating Instructions:

The EF 400 is a 400 watt fog machine. It is primarily used to enhance lighting effects. Begin by removing all of the packing material, especially around the nozzle area. Set the fog machine on a flat, dry surface. Fill the fog juice reservoir, using Eliminator brand Water Based Fog Juice, only. Attach the included remote control to the unit. Plug the unit into a matching power outlet, and press the power switch to the "On" position. A red L.E.D. will glow on the remote control indicating that the unit is receiving power. Wait for about 5 minutes for the unit to heat up. After the unit has heated up, the red L.E.D. will turn off on the remote control, indicating that the unit is ready. Push the button on the remote control to emit fog.

1 Year Limited Warranty: Eliminator Lighting warranty is valid from the date of purchase. Our 1 year limited warranty covers manufacturing defects only. Serial number, place of purchase with dated valid receipt must be submitted at time of service. Eliminator Lighting warranty does not cover items or parts prone to wear and tear: lamps, fuses, brushes and belts. Eliminator Lighting warranty is only valid with-in the United States.

SAFETY ISSUES:

NEVER POINT OR AIM A FOG MACHINE TOWARDS PEOPLE OR THEIR CLOTHING. THIS UNIT EMITS HOT VAPOR AND SHOULD BE USED WITH THE SAME CARE THAT YOU WOULD OBSERVE WHEN USING AN ELECTRIC IRON.