

EDIT PARAMETERS

Category	Abbreviated name	Description	Function	Values	Default setting
Tuning	Fine tuning	General fine tuning in 1/5-Hz steps	E 1	427 - 453	440
Tuning	Tuning	Selection of temperament (scale)	E 2.1	1 → 7	1 (equal temper)
	Basic note	Selection of basic note of temperament	E 2.2	c → b	c
Layer mode	Volume	Volume ratio of voice #1 vs. voice #2	E 3.1	0 → 20	-*
	Detune	Detuning of voice #1 vs. voice #2	E 3.2	- 10 → 10	-*
	Octave transposition voice #1	Octave position of voice #1	E 3.3	- 1, 0, 1	-*
	Octave transposition voice #2	Octave position of voice #2	E 3.4	- 1, 0, 1	-*
	Effect intensity voice #1	Portion of voice #1 volume channeled to the effect	E 3.5	0 → 20	-*
	Effect intensity voice #2	Portion of voice #2 volume channeled to the effect	E 3.6	0 → 20	-*
	Reset	Reset of layer mode settings	E 3.7	-	-
Soft pedal	Function	Function of soft pedal: 1) soft pedal, 2) music sequencer	E 4.1	1, 2	1
	Effect	Intensity of soft pedal on sound	E 4.2	1 → 5	3
Metronome	Volume	Volume of metronome click	E 5	1 → 20	10
Sequencer	Dimmed volume	Volume of the muted track in music sequencer mode	E 6	0 → 20	5
MIDI	Transmit channel	MIDI channel on which MIDI data are transmitted	E 7.1	1 → 16, oFF	1
	Receive channel	MIDI channel on which MIDI data are received	E 7.2	ALL, 1-2, 1 → 16	ALL
	Sound generator (Local on/off)	Enables/disables the built-in sound generator for keyboard data	E 7.3	on, oFF	on
	Program change	Accept or ignore program change data (send/receive)	E 7.4	on, oFF	on
	Controller commands	Accept or ignore controller commands (send/receive)	E 7.5	on, oFF	on
	Transposition	Transposition of notes during MIDI transmission	E 7.6	- 12 → 12	0
	Control panel settings	MIDI transmission of all current settings (dump)	E 7.7	-	-
	Music sequencer data	MIDI transmission of music sequencer data (dump)	E 7.8	-	-
Save	Sounds	Permanent saving of sound settings	E 8.1	on, oFF	oFF
	MIDI	Permanent saving of MIDI settings	E 8.2	on, oFF	oFF
	Tuning	Permanent saving of transposition and tunings	E 8.3	on, oFF	oFF
	Soft pedal	Permanent saving of soft pedal settings	E 8.4	on, oFF	oFF

* Default settings depend on the selected sound combination.

