White PreSonus

Setting Up Your PreSonus Device in Cubase LE4

When you receive your PreSonus interface and open Cubase LE4 for the first time, you'll need to set up all of your input and output busses.

1. Open Cubase, and go to the "Devices/Device Setup" window. Click on "VST Audio System" and select your PreSonus interface.

(• (ubas	e LE 4											
File	Edit	Project	Audio	MIDI	Media	Transport	Devices	Window	Help				
							MIDI D	evice Mar	nager				
							Mixer			F3			
							Plug-in	ı Informati	ion				
							VST Co	onnections	;	F4			
							VST Pe	erformance	э	F12			
							Video			F8			
							Show F	Panel					
							Device	Setup					

2. In "Device Setup", click on "VST Audio System" and select your PreSonus interface as your ASIO driver. When asked if you want to "keep" or "switch" the audio driver, select "switch" and then press "OK", to close.

+ - 14	VST Audio System
Devices	ASIO PreSonus FireStudio - ASID Driver
→ MIDI → O MIDI Port Setup → Video → ¥32 Video Player → VST System Link	 Release Driver when Application is in Background Input Latency: 12.854 ms Output Latency: 17.167 ms
	Advanced Options Set to Defaults High Audio Priority 2 Seconds Disk Preload I Lower Latency Multi Processing Adjust for Record Latency Record Shift
<	Help Reset Apply

M PreSonus

3. Go back to "Devices" and then to "VST Connections"



4. In the "Inputs" tab, delete any existing busses. Then add a Mono Bus for every channel, in this case, 16 mono busses.

Cubase LE 4	a da taran sa da	Taxana Da	The standard state				
Hie Eait Project	Audio MLDI Media	Transport De	vices window Help				
	📀 VST Connectio	ns - Inputs					_ 🗆 🛛
	Inputs Outpu	Add Bus	Presets -				
	Bus Name	Speakers	Audio Device	Add Input Bus Mono M 16 OK	Configuration		~
		nal (MDI) - R		1. 1. ⁻ ≪ ≫ >	I. 0 ↓ > □ > ●	CLICK OFF IIM TEMPO TRACK 4/4 120.000 SVHC INT. Offline	

M PreSonus

5. Make sure that the "Device Port" column has your inputs number 1-16, top to bottom

VST Connections	Inputs			
Inputs Dutputs	19u	Preset:	6	
But Name	Speakers	Audo Device	Device Post	100
E d Mone In	Marter	ASIO PreSonus FeeStudio		
-e Mono			FIRESTUDIO Mic/trut 1	
Mono In 2	Hare :	ASID PreSional FeeShado		
Mono			FIRESTUDIO Mic/mit 2	
El Mono In 3	Mater	ASIO PreSonui FeeStudio		
e Mono		10000	FIRESTUDIO MCALINE 3	
Mone in 4	Mone	Abru PreSonui FreShudo	PROTECTION AND A DOWN	
Mono	10	Atto Datas Cafe da	FINESTODIO MIC/Line 4	
Mono in s	Hure .	Para President President	DBFSTUDIO Medica 5	
Mana In F	1 Marco	ASID Decisions Francis da	THE STODY PROCESS	
in Mont	11000	Hard President President	DEFETUDIO Mail and F	
Mana In 7	C Married	ASID Prefares Feelbacks	THE STOLEN MENTERS	
- More			FIRESTUDIO MicA en 7	
- Mono In B	Mare	ASID PreSonus FireStudio		
Mono			FIRESTUDIO Michine 8	
Mono In S	Mane	ASIO PreSonus FeeStudio	A MARTINE MARTINE	
-a Mono	Contra a	a state the second state	FIRESTUDIO ADAT 1	
Mono In 10	Mana	ASIO PreSorun FeeStudio	Manufacture and a second	
o Mono	1024		FIFIESTUDIO ADAT 2	
More In 11	Manu	ASIO PreSona FreShado	A CARLEN AND A CARL	
	1000		FIRESTUDIO ADAT 3	
Mono in 12	Horse :	ASID PreSorue FeeStudio		
- Mono	-		FIRESTUDIO ADAT 4	
Mono In 13	Marie	ASIQ Piesonul Fieshudo	60000 0000 00000 0	
e Mono	10.00	1000.0.000.000	FPIESTUDIO ADAT 5	
Mone In 14	Hars	April Presonal Freshado	DOTOTIONO ADATIO	
Mono	No.	ADD Defense Fields de	FPIESTOUR ADAT 6	
Peppo at 15	POPE .	HOLD PREPARED PREPARED	EDECTUDIO ADAT Y	
Mano In 16	Advenue 1	ASIO ParSona Emiliada	THE STOLIG NEWLY	
- Hone Hone		Hord Preparati Perpada	EDESTUDIO ADAT 8	
2 HOL			The state of the second s	*
()				2

6. Once that's done. Go to "File/New Project" to create a new project. After that, click "Project/Add Track/Audio" to create your audio tracks



M PreSonus

7. Create a mono channel for every mono bus that you created in "VST Connections"

🔆 Add Audio Track 🛛 🔀
Audio Track Configuration
16 Mono M count configuration speakers
OK Cancel

8. From there, select each channel's input and output bus. Here, we're selecting "Mono In 2" for channel 2.



9. Make sure that the "Record Enable" and "Monitor" buttons are engaged.

If you have any other questions, contact PreSonus Tech Support at 1-800-750-0323 or at <u>techsupport@presonus.com</u>